

FIRE ALARM CONTROL PANEL

CE-30-01-04

EDU-LABS



SPECIFICATION

- Main & D/C on indication
- Main fail indication
- Battery fail indication
- Charger fail indication
- Bell line fail indication
- Zone fire, fault & isolate indication
- Evacuate switch & indication
- Buzzer isolate switch & indication
- Bell isolate switch & indication
- Fire station isolate & indication
- Auxiliary trip isolate switch & indication
- Main on / off switch
- Test lamp switch
- Test zone alarm, fault & isolate switch
- Test battery push button switch
- Master reset push button switch

TECHNICAL DATA

4 zones fire alarm control panel c/w built in charger

- Power supply input : 240V AC 50Hz
- Charger : Auto / Trickle
- End of line : 8K2 Ohms
- CMS output : N/O Contact
- Operating / System : 24V DC
- Charging rate : 300mA / 2.5A (Boost)
- Auxiliary output : 24V, 1 Amp
- Current spec : Standby Mode - Master: 75mA, per zone c/w detector: 5mA
- Alarm Mode - Master : 140mA, per trigger zone: 70mA
- Output devices (typical) : 200mA, per bell: 30mA
- 2 units Standby battery 12V/2.3Ah

Note: Due to products continuous development process, layout and specification may change without prior notices.